



Kane International Limited Kane House, Swallowfield, Welwyn Garden City, Hertfordshire, AL7 1JG, UK T: +44 (0) 1707 375550 F: +44 (0) 1707 393277 E: sales@kane.co.uk

KANE455 Bluetooth™ Communication



Stock No. 19081

August 2011

© Kane International Ltd

Bluetooth™ Communication with Pass Key

1: Power up the KANE455 and allow to fresh air purge.



9: Select exit and rotate the dial to Ratio.

Pairing with Laptop / PC – Windows 7

1: Open the Bluetooth[™] Manger



2: Select ADD DEVICE.



3: Select the KANE455 from the list and click next.

4: Select Enter the device pairing code.



5: Enter the pairing code you set on the KANE455 e.g.1111.



6: This message will appear.



7: Select the paired KANE455 press the right hand mouse key, select the properties to see the com port.

Kane 425 Properties	×				
General Hardware Services Bluetooth					
Kane 425					
Device Functions:					
Name	Туре				
The Standard Serial over Bluetooth link (COM21)	Ports (COM				
Device Function Summary					
Manufacturer: Microsoft					
Location: on Bluetooth Device (RFCOMM Protocol TDI)					
Device status: This device is working properly.					
	Properties				

8: Select ok.

Pairing with Laptop / PC – Windows XP

1: Click the Bluetooth[™] icon on the taskbar followed by: Add a Bluetooth Device. This opens the Add Bluetooth device Wizard



2: Tick "My device is set up and ready to be found" and click "Next"



3: Highlight the device you wish to add and click "Next" (if your device is not found Search again).

Add Bluetooth Device Wizard 🛛 🛛 🔀						
Do you need a passkey to add your device?	×					
To answer this question, refer to the "Bluetooth" section of the documentation that came with your device. If the documentation specifies a passkey, use that one.						
O Choose a passkey for me						
\bigcirc Use the passkey found in the documentation:						
⊙ <u>L</u> et me choose my own passkey:	1111					
O Don't use a passkey						
You should always use a <u>passkey</u> , unless your device does not support one. We recommend using a passkey that is 8 to 16 digits long. The longer the passkey, the more secure it will be.						
< <u>B</u> ack <u>N</u> ext > Cancel						

4: Select "let me chose my own passkey" and enter the code you set on the KANE455 e.g. 1111. Then click Next and this message will appear:

Add Bluetooth Device Wizard					
®	Completing the Add Bluetooth Device Wizard The Bluetooth device was successfully connected to your computer. Your computer and the device can communicate whenever they are near each other.				
	These are the COM (serial) ports assigned to your device.				
	Outgoing COM port: COM60				
	Incoming COM port: COM66				
	Learn more about <u>Bluetooth COM ports</u> .				
	To close this wizard, click Finish.				
	< <u>B</u> ack Finish Cancel				

5: Note the <u>Outgoing</u> COM port number and click Finish.

KANE425 PC Software

1: Open the KANE425 PC software and select the com port and then connect.

K15 Set	connected to Com 21								
Select Port Number	Help Print	Com Port	Connect	ombn Combn	Pressure	Tight ^{ns}	Temp		Info
	J								
Status: Connecte	d								

2: Connected will appear in the bottom left hand corner.

